


CARGA BATERÍA LITIO EN MOTOS GAS GAS

La batería (Skyrich HJTZ5S-FP) es sin mantenimiento de 12v / 1.0-10.0 (A) / 120 CCA.



DATOS DE CARGA

1. Utilizar siempre un **cargador especial para baterías de litio (LiFePO4) de 12.8V.**
 2. La moto se entrega de fábrica con una carga del 40-60%. Antes de poner la moto en condiciones de uso, se debe cargar hasta el 100% de su carga.
 3. Cuando termine la carga, se debe desenchufar el cargador de la batería.
-
- A. Recargar la batería periódicamente.
 - B. Tensión mínima antes de comenzar el proceso de carga 9v.
 - C. Una vez cargada, dejar la batería entre 1 a 2 horas antes de comprobar el voltaje. Si es menor de 10v cambiarla.
 - D. Si no se utiliza la motocicleta, recargar cada 3 meses.

IMPORTANTE!

No manipule ni intente abrir la batería: el electrolito y los gases son tóxicos y pueden causar lesiones graves.

Mantenga la batería fuera del alcance de los niños.

Mantenga la batería lejos de fuentes de calor, llamas abiertas y chispas.

Almacenar y cargar siempre la batería en lugares bien ventilados.

LITHIUM BATTERY CHARGE IN GAS GAS BIKES

Battery "Skyrich HJTZ5S-FP" is, without maintenance, of 12v / 1.0-10.0 (A) / 120 CCA.



CHARGE DETAILS

1. Use always an **special charger for lithium batteries (LiFePO4) of 12.8V.**
 2. The bike is delivered from factory with a charge of 40-60%. Before getting the bike in user conditions, the battery should be completely charged to 100%.
 3. When the charge is finished, the charger should be disconnected from battery.
-
- A. Charge the battery periodically.
 - B. Minimum tension before starting the charge: 9v.
 - C. Once the battery is charged, leave the battery 1-2 hours before checking the voltage. If it is lower than 10v, it should be replaced.
 - D. If you don't use the bike, recharge the battery every 3 months.

IMPORTANT!

Do not open the battery: electrolyte and gases are toxic and can cause serious injuries.

Keep the battery away from children.

Keep the battery away from heat sources, open flames and sparks.

Stock and charge the battery always in well-ventilated spaces.